

JDYX2.E197390 - Fuses, Supplemental - Component

Fuses, Supplemental - Component

See General Information for Fuses, Supplemental - Component

OPTIFUSE

E197390

SUITE C

1675 PIONEER WAY

EL CAJON, CA 92020 USA

Supplemental fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
FCA	6.35 x 31.75 (0.25 x 1.25)	15.1 - 20	250Vac	750
		15.1 - 20	125Vac	10000
		15.1 - 20	250Vdc	750
		20.1 - 30	250Vac	100
		20.1 - 30	125Vac	1000
		20.1 - 30	125Vdc	400
		20.1 - 30	75Vdc	1000
FCD-P	5.2 x 20 (0.20 x 0.79)	0.063 - 4	250Vac	1500
		5 - 6.3	250Vac	1500
		8 - 10	250Vac	1500
		0.063 - 4	125Vac	400
		5 - 6.3	125Vac	400
		8 - 10	125Vac	400
		12.5	125Vac	400
		0.063 - 4	250Vac	400
		5 - 6.3	250Vac	400
		8 - 10	250Vac	400

		12.5	250Vac	400
		0.063 - 4	300Vac	400
		5 - 6.3	300Vac	400
		8 - 10	300Vac	400
		12.5	300Vac	400
		0.063 - 4	350Vac	400
		5 - 6.3	350Vac	400
		8 - 10	350Vac	400
		12.5	350Vac	400
		0.063 - 4	400Vac	400
		5 - 6.3	400Vac	400
		8 - 10	400Vac	400
		12.5	400Vac	400
		12.6 - 16	125Vac	200
		12.6 - 16	250Vac	200
		12.6 - 16	300Vac	200
		12.6 - 16	350Vac	200
		12.6 - 16	400Vac	200
		0.063 - 4	125Vdc	300
		5 - 6.3	125Vdc	300
		8 - 10	125Vdc	300
		12.5 - 16	125Vdc	300
		0.063 - 4	250Vdc	300
		5 - 6.3	250Vdc	300
		8 - 10	250Vdc	300
		12.5 - 16	250Vdc	300
		0.063 - 4	300Vdc	300
		5 - 6.3	300Vdc	300
		8 - 10	300Vdc	300
		12.5 - 16	300Vdc	300

		0.063 - 4	350Vdc	300
		5 - 6.3	350Vdc	300
		8 - 10	350Vdc	300
		12.5 - 16	350Vdc	300
		0.063 - 4	400Vdc	300
		5 - 6.3	400Vdc	300
		8 - 10	400Vdc	300
		12.5 - 16	400Vdc	300
FPL, FMR-E, FMS-E, TPL, TMR-E, TMS-E, FMR-E, FMS-E				
	8.4 x 8.3 (0.33 x 0.33)	0.05 - 3.15	277Vac	35
		0.04 - 3.15	277Vac	35
		4 - 6.3	277Vac	10x Ampere rating
FSA	6.35 x 31.8 (0.25 x 1.25)	12 - 30	250Vac	100
		12 - 30	125Vac	200
		12 - 30	32Vac	300
FSD	5.2 x 20 (0.20 x 0.79)	0.063 - 0.1	250Vac	35
		0.125 - 3.15	250Vac	35
		4 - 6.3	250Vac	100
		8 - 10	250Vac	100
FSG	10.3 x 38.1 (0.41 x 1.50)	4 - 30	32Vac	300
FSX	6.35 x 31.8 (0.25 x 1.25)	12 - 20	32Vac	300
SCA	6.35 x 32 (0.25 x 1.26)	1 - 20	500Vac	200
		21 - 30	500Vac	100
SCC	5.2 x 20 (0.20 x 0.79)	1 - 20	250Vac	200
TCA	6.35 x 31.8 (0.25 x 1.25)	15.1 - 20	125Vac	10000

		15.1 - 20	250Vac	400
		20.1 - 30	125Vac	10000
		20.1 - 30	125Vdc	10000
		20.1 - 30	250Vac	1500
TCD	5.2 x 20 (0.20 x 0.79)	0.5 - 10	250Vac	1500
TCM	6.2 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.2 - 7	125Vac	50
		0.2 - 7	125Vdc	50
		0.2 - 7	32Vdc	300
TSA	6.35 x 32 (0.25 x 1.26)	10.1 - 30.0	32Vac	1000
TSC-LS	5.2 x 20 (0.20 x 0.79)	0.5 - 6.3	250Vac	150
TSD	5.2 x 20 (0.20 x 0.79)	1 - 3.15	250Vac	35
		4 - 10	250Vac	100

Supplemental fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
FCA-P	6.35 x 31.75 (0.25 x 1.25)	15.1 - 20	250Vac	750
		15.1 - 20	125Vac	10000
		15.1 - 20	250Vdc	750
		20.1 - 30	250Vac	100
		20.1 - 30	125Vac	1000
		20.1 - 30	125Vdc	400
		20.1 - 30	75Vdc	1000
FSA-P	6.35 x 31.8 (0.25 x 1.25)	12 - 30	250Vac	100
		12 - 30	125Vac	200
		12 - 30	32Vac	300
TCA-P	6.35 x 31.8	15.1 - 20	125Vac	10000

	(0.25 x 1.25)			
		15.1 - 20	250Vac	400
		20.1 - 30	125Vac	10000
		20.1 - 30	125Vdc	10000
		20.1 - 30	250Vac	1500
TSE-P, TSE-LSP	4.6 x 14.5 (0.18 x 0.57)	3.75 - 8.0	250Vac	200

Supplemental fuses: cartridge enclosed

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
FCD	5.2 x 20 (0.20 x 0.79)	10.1 - 12.5	250Vac	1500
		12.6 - 16	250Vac	1500

Supplemental fuses: pigtail leads

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
FCL-P	5.2 x 20 (0.20 x 0.79)	0.05 - 3.15	250Vac	10x Ampere rating
		4 - 6.3	250Vac	35
FSD-P	5.2 x 20 (0.20 x 0.79)	0.063 - 0.1	250Vac	35
		0.125 - 3.15	250Vac	35
		4 - 6.3	250Vac	100
		8 - 10	250Vac	100
FSE-BP	4.6 x 14.5 (0.18 x 0.57)	0.01 - 3.5	350Vac	100
		0.01 - 3.5	140Vdc	100
		3.6 - 8	350Vac	100
FSL-P	3.9 x 11 (0.15 x 0.43)	0.25 - 6.3	250Vac	35
		0.25 - 6.3	250Vac	10x Ampere rating
SCA-P	6.35 x 32 (0.25 x 1.26)	1 - 20	500Vac	200

		21 - 30	500Vac	100
SCC-P	5.2 x 20 (0.20 x 0.79)	1 - 20	250Vac	200
TCD-P	5.2 x 20 (0.20 x 0.79)	0.5 - 10	250Vac	1500
TCL-P	4 x 10 (0.16 x 0.39)	0.25 - 3.15	250Vac	35
		4 - 6.3	250Vac	10x Ampere rating
TSD-P	5.2 x 20 (0.20 x 0.79)	1 - 3.15	250Vac	35
		4 - 10	250Vac	100
TSE-P	4.6 x 14.5 (0.18 x 0.57)	3.75 - 8	250Vac	200
TSL-P	5.2 x 20 (0.20 x 0.79)	0.25 - 6.3	250Vac	35
		0.25 - 6.3	250Vac	10x Ampere rating

Supplemental micro fuses

Cat. No.	Size mm(in)	Amps (A)	Volts (V)	Interrupting Rating (A)
FCM	6.2 x 2.6 x 2.6 (0.24 x 0.10 x 0.10)	0.062 - 8	125Vac	50
		0.062 - 8	32Vdc	300
		8.1 - 10	125Vac	35
		8.1 - 10	125Vdc	50
		8.1 - 10	32Vdc	300
		12 - 15	65Vac	50
		12 - 15	65Vdc	50
		12 - 15	24Vdc	300
FMR-R-E	8.35 x 4.3 x 7.7 (0.33 x 0.17 x 0.30)	0.05 - 3.15	250Vac	35
		4 - 5	250Vac	10x Ampere rating
		6.3	250Vac	10x Ampere rating
FMS-R-E	8.35 x 4.3 x 7.7 (0.33 x 0.17 x 0.30)	0.05 - 3.15	250Vac	35

		4 - 5	250Vac	10x Ampere rating
		6.3	250Vac	10x Ampere rating
FXG	8.6 x 3.2 (0.34 x 0.13)	0.1 - 10.0	125Vac	50
		0.1 - 10.0	125Vdc	300
		10.1 - 15	32Vac	50
		10.1 - 15	32Vdc	300
FXH	13.5 x 3.5 (0.53 x 0.14)	0.1 - 5	250Vac	50
TMR-R-E	8.35 x 4.3 x 7.7 (0.33 x 0.17 x 0.30)	0.04 - 6.3	300Vac	50
		0.04 - 6.3	400Vac	100
		0.04 - 6.3	250Vdc	100
		0.04 - 6.3	250Vac	130
		0.04 - 3.15	250Vac	35
		4 - 6.3	250Vac	10x Ampere rating
		6.3	300Vac	63
		8 - 10	250Vac	10x Ampere rating
		8	300Vac	80
		10	300Vac	100
		8 - 10	300Vac	50
		8 - 10	400Vac	100
		8 - 10	250Vdc	100
		8 - 10	250Vac	130
		0.04 - 6.3	500Vac	100
		8 - 10	500Vac	100
TMS-R-E	8.35 x 4.3 x 7.7 (0.33 x 0.17 x 0.30)	0.04 - 6.3	300Vac	50
		0.04 - 6.3	400Vac	100
		0.04 - 6.3	250Vdc	100
		0.04 - 6.3	250Vac	130

		0.04 - 3.15	250Vac	35
		4 - 6.3	250Vac	10x Ampere rating
		6.3	300Vac	63
		8 - 10	250Vac	10x Ampere rating
		8	300Vac	80
		10	300Vac	100
		8 - 10	300Vac	50
		8 - 10	400Vac	100
		8 - 10	250Vdc	100
		8 - 10	250Vac	130
		0.04 - 6.3	500Vac	100
		8 - 10	500Vac	100
TXG	13.5 x 3.5 (0.53 x 0.14)	0.5 - 5	125Vac	50
		0.5 - 5	125Vdc	50
TXH	13.5 x 3.5 (0.53 x 0.14)	0.375 - 7	250Vac	50
		0.375 - 7	125Vdc	50

Marking: Company name and model designation.

Last Updated on 2020-02-11

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2022 UL LLC."